



Dictaphone Freedom DST Change

1. From a command prompt, telnet into Freedom IP address.
2. Login to system using account logger, logger.

```
GA Telnet 10.1.2.26
Dictaphone Freedom < BEI >                               Main Menu
Press a number to make a selection, ESC to End Session

1. Configure Network Parameters
2. Configure Telecom Block
3. Configure Recorder
4. Equipped Channel
5. Service
6. Status Report
7. Administration
8. Lock System
9. Unlock System/Save to EEPROM
A. Exit to Shell

Version 1.2.12F CM-----STATUS BAR-----LOCKED-----
Configure Network Parameters
```

3. Select option 8. Lock System.
4. Select option 2. Configure Telecom Block.

```
GA Telnet 10.1.2.26
Dictaphone Freedom < BEI >                               Telecom Block Configuration Menu
Press a number to make a selection, ESC to Previous Screen

1. Get TB Configure Parameters
2. Set TB Configure Parameters
3. TB Online
4. TB Offline
5. Get TB Date Time
6. Set TB Date Time
7. Get TB Daylight Saving Time
8. Set TB Daylight Saving Time

Version 1.2.12F CM-----STATUS BAR-----LOCKED-----
Get TB Configure Parameters
```

5. Select option 4. TB Offline.
6. Select option 8. Set TB Daylight Saving Time.
7. Change the Enter and Exit DST parameters to match the following:



```
ca Telnet 10.1.2.26
Dictaphone Freedom < BEI > Daylight Savings Time Configuration Screen
Press ESC for Previous Screen, TAB to Change Field, ENTER to Save
DST Enabled:1 Disabled:0
DST Enabled      1
DST Offset      60
Enter DST:
Day Of Week     0
Day In Month    2
Date <day>       0
Date <month>     3
Time            02:00:00
Exit DST:
Day Of Week     0
Day In Month    1
Date <day>       0
Date <month>     11
Time            02:00:00
```

8. Once changes have been, press enter to save.
9. Select option 3. TB Online.
10. Press ESC to exit to main screen.
11. Select option 9. Unlock System/Save to EEPROM.
12. Select option A. Exit to Shell.